

TH32 Instruction Set

(Version 0.09.0, 30 Mar. 1998)

1 Arithmetics

instruction	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0			
ADD	1	1	dest				0	0	1	0	0	0	0	0	0	0	operand1						operand2												
ADDC	1	1	dest				0	0	1	1	0	0	0	0	0	0	operand1						operand2												
SUB	1	1	dest				0	0	0	0	0	0	0	0	0	0	operand1						operand2												
SUBB	1	1	dest				0	0	0	1	0	0	0	0	0	0	operand1						operand2												
CMP	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	operand1						operand2													
AND^f	1	1	dest				0	1	0	0	0	0	0	0	0	0	operand1						operand2												
OR^f	1	1	dest				0	1	0	1	0	0	0	0	0	0	operand1						operand2												
XOR^f	1	1	dest				0	1	1	0	0	0	0	0	0	0	operand1						operand2												
TEST^f	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	operand1						operand2													
MOV^f	1	1	dest				0	1	0	1	0	0	0	0	0	0	operand						1	0	0	0	0	0	0	0	0	0	0	0	0
NOT^f	1	1	dest				0	1	1	0	0	0	0	0	0	0	operand						1	1	1	1	1	1	1	1	1	1	1	1	
UNIHL^f	1	1	dest				0	1	1	1	0	0	0	0	0	0	operand1						operand2												
UNIHH^f	1	1	dest				0	1	1	1	0	1	0	0	0	0	operand1						operand2												
MOVHL	0	1	dest				0	1	1	1	0	1	0	0	0	0	0	0	0	0	0	0	operand												
SER1^f	1	1	dest				1	0	0	0	0	0	0	0	0	0	operand1						operand2												
SHR1^f	1	1	dest				1	0	1	0	0	0	0	0	0	0	0	0	0	0	0	operand													
SER8^f	1	1	dest				1	0	0	1	0	0	0	0	0	0	operand1						operand2												
SHR8^f	1	1	dest				1	0	0	1	0	0	0	0	0	0	operand						1	0	0	0	0	0	0	0	0	0	0	0	

SER1 $d := [o1:o2] \rightarrow 1$

SER8 $d := [o2:o1] \rightarrow 8$

UNIHy $d_H := o1_H, d_L := o2_y$

MOVHL, MOVLH hazard can be removed using **UNIHH, UNILL** in some case.

2 Memory

instruction	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
STORE	0	0	0	0	0	0	1	1	0	1	0	0	0	0	0	0	ope1(data)						ope2(addr)									
ADDR	0	0	0	0	0	0	1	1	1	0	1	0	0	0	0	0	operand															
MUL20	0	0	0	0	0	0	1	1	1	1	0	0	1	1	0	0	operand1						operand2									
MUL21	0	0	0	0	0	0	1	1	1	1	0	0	1	0	0	0	operand1						operand2									
MUL22	0	0	0	0	0	0	1	1	1	1	0	1	1	1	0	0	operand1						operand2									
MUL23	0	0	0	0	0	0	1	1	1	1	0	1	1	0	0	0	operand1						operand2									
MUL30	0	0	0	0	0	0	1	1	1	1	0	0	0	1	0	0	operand1						operand2									
MUL31	0	0	0	0	0	0	1	1	1	1	0	0	0	0	0	0	operand1						operand2									
MUL32	0	0	0	0	0	0	1	1	1	1	0	1	0	1	0	0	operand1						operand2									
MUL33	0	0	0	0	0	0	1	1	1	1	0	1	0	0	0	0	operand1						operand2									
LOAD	1	1	dest				1	1	1	0	0	0	0	0	1	1	0															
LOADH0	1	1	dest				1	1	1	0	0	0	0	0	1	0	0															
LOADH	1	0	dest				1	1	1	0	0	0	0	0	1	0	0															
LOADL0	1	1	dest				1	1	1	0	0	0	0	0	1	0	0															
LOADL	0	1	dest				1	1	1	0	0	0	0	0	1	0	0															

LOAD LOAD instruction can be combined with MUL* and ADDR by bitwise OR

3 Branch, Set

instruction	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
SETH	1	0	dest			1	1	0	0	0	0	0	0	1	0	Imm16																
SETH0	1	1	dest			1	1	0	0	0	0	0	0	1	0	Imm16																
SETL	0	1	dest			1	1	0	0	0	0	0	0	0	1	Imm16																
SETL0	1	1	dest			1	1	0	0	0	0	0	0	0	1	Imm16																
SHL16	1	1	dest			1	1	0	0	0	0	1	0	1	0	0	0	0	0	0	0	operand										
SHR16	1	1	dest			1	1	0	0	0	1	1	0	0	1	0	0	0	0	0	operand											
BA	0	0	0	0	0	0	1	1	0	0	1	0	0	1	0	0	Imm16															
BA	0	0	0	0	0	0	1	1	0	0	1	0	1	1	0	0	0	0	0	0	operand											
BN	0	0	0	0	0	0	1	1	0	0	1	0	0	0	0	Imm16																
BN	0	0	0	0	0	0	1	1	0	0	1	0	1	0	0	0	0	0	0	operand												
BE	0	0	0	0	0	1	1	1	0	0	1	0	0	0	0	Imm16																
BE	0	0	0	0	0	1	1	1	0	0	1	0	1	0	0	0	0	0	0	operand												
BNE	0	0	0	0	0	1	1	1	0	0	1	0	0	1	0	Imm16																
BNE	0	0	0	0	0	1	1	1	0	0	1	0	1	1	0	0	0	0	0	operand												
BG	0	0	1	0	0	1	1	1	0	0	1	0	0	1	0	Imm16																
BG	0	0	1	0	0	1	1	1	0	0	1	0	1	1	0	0	0	0	0	operand												
BGE,BC	0	0	1	0	0	0	1	1	0	0	1	0	0	1	0	Imm16																
BGE,BC	0	0	1	0	0	0	1	1	0	0	1	0	1	1	0	0	0	0	0	operand												
BL,BNC	0	0	1	0	0	0	1	1	0	0	1	0	0	0	0	Imm16																
BL,BNC	0	0	1	0	0	0	1	1	0	0	1	0	1	0	0	0	0	0	0	operand												
BLE	0	0	1	0	0	1	1	1	0	0	1	0	0	0	0	Imm16																
BLE	0	0	1	0	0	1	1	1	0	0	1	0	1	0	0	0	0	0	0	operand												
BSG	0	0	0	1	1	1	1	1	0	0	1	0	0	1	0	Imm16																
BSG	0	0	0	1	1	1	1	1	0	0	1	0	1	1	0	0	0	0	0	operand												
BSGE	0	0	0	1	1	0	1	1	0	0	1	0	0	1	0	Imm16																
BSGE	0	0	0	1	1	0	1	1	0	0	1	0	1	1	0	0	0	0	0	operand												
BSL	0	0	0	1	1	0	1	1	0	0	1	0	0	0	0	Imm16																
BSL	0	0	0	1	1	0	1	1	0	0	1	0	1	0	0	0	0	0	0	operand												
BSLE	0	0	0	1	1	1	1	1	0	0	1	0	0	0	0	Imm16																
BSLE	0	0	0	1	1	1	1	1	0	0	1	0	1	0	0	0	0	0	0	operand												
BPOS	0	0	0	1	0	0	1	1	0	0	1	0	0	1	0	Imm16																
BPOS	0	0	0	1	0	0	1	1	0	0	1	0	1	1	0	0	0	0	0	operand												
BNEG	0	0	0	1	0	0	1	1	0	0	1	0	0	0	0	Imm16																
BNEG	0	0	0	1	0	0	1	1	0	0	1	0	1	0	0	0	0	0	0	operand												

B* branch instructions have 2 branch delay slots.

4 Remarks

All Instructions are executed with 1-clock.

All instructions have 1 result latency on result-value and no latency on flags. Specified explicitly, results of instructions maked by ¶ can be used as 2nd-operand of next instruction.

Credits

©1997–1998 Char-han Project. Rights for this document is reserved.